



# Dire Wolf Software TNC

John Langner, WB2OSZ  
ATGP, December 14, 2021



# Topics

- History: Packet Radio. What is a TNC?
- Main Theme: Replace old hardware TNC with only software.
- Building a better demodulator.






# Radio + Teletype = RTTY



Simple  
Modem

Audio &  
PTT



Modem was called a "terminal unit".

170 Hz AFSK

AFSK → SSB → RF FSK



# Packet Radio - 1978

- Radical new concept.
- Montreal Amateur Radio Club.
- Vancouver Area Digital Communications Group.
- Each transmission was a short burst (“packet” or “frame”) containing:

Flag	Address	Control	Info	FCS
01111110	112/224 Bits	8/16 Bits	N*8 Bits	16 Bit



# Packet Radio


Modem &  
packet protocol



RS-232



Audio &  
PTT



Terminal Node Controller (TNC).


Modem + brains.



# Advantages of Packet Radio

- Short bursts.
- Addresses.
- Shared channel.
- Error detection.
- ACK & retry – for “connected” mode.
- Repeaters.
- “Transparent” for “binary” data.

# TAPR TNC-1 kit - 1983





# Dumb Terminal to Human Interface

```
K1OJH>ALL,W0RLI*:NEPRA meeting tonight at 7:00
```

```
cmd> c k7ve
```

```
*** CONNECTED to K7VE
```

```
I will bring the cable that you need tonight.
```

```
Great! See you there.
```

```
(ctrl-C)
```

```
cmd> d
```

```
*** DISCONNECTED from K7VE
```

Not good for computer control.



# K.I.S.S. Protocol - 1986



RS-232



Very simple  
(KISS) TNC



Address	Control	
112/224 Bits	8/16 Bits	N*

Flag	Address	Control	Info	FCS
01111110	112/224 Bits	8/16 Bits	N*8 Bits	16 Bit

Smaller brain needed for TNC.

- Transmit: TNC adds CRC and HDLC flags.
- Receive: TNC checks for correct CRC and removes it.



# APRS – Data Types

*“APRS is not a vehicle tracking system. ...”*

- Positions (usually transmitting station.)
- Objects (usually on behalf of other entity.)
- Weather Reports.
- Telemetry.
- “Messages” to an individual or bulletins to groups.
- Queries and Responses.
- APRS of Things. (like Internet of Things)



# Packet / APRS – late 20<sup>th</sup> Century



Hardware TNC  
from 1980's

RS-232






# TNC replaced by software



Audio &  
PTT





Cheaper.

Better Results.


# More Flexibility



APRSDroid,  
APRSISCE,  
YAAC,  
Xastir, UISS,  
APRS-TW,  
WinLink  
Express,  
Outpost PM,  
etc.



Raspberry Pi  
TNC software.





# What is Dire Wolf ?

Free Open source software replacement for the traditional TNC.


- Windows, 32 or 64 bit.
- Linux - x86, x86\_64 PC, ARM, Raspberry Pi.
- Mac OSX, BSD.
  
- GPS Tracker.
- Digipeater.
- Internet Gateway (IGate).
- APRStt gateway.
  
- Virtual TNC for applications such as APRSIS32, YAAC, Xastir, SARTrack, PinPoint, APRS, APRS-TW, UISS, Linux\_AX25, WinLink Express (RMS Express), Outpost PM, Linpac, and many others.




# Where did the name come from?


Decoded  
Information from  
Radio  
Emissions for

Windows  
Or  
Linux  
Fans





Receiver audio → computer.  
Computer audio → transmitter.





# Software Defined Radio (SDR) Interface


- Pipe into stdin

```
rtl_fm -f 144.39M | direwolf -
```

- Listen for audio on a UDP port.

(e.g. `gqrx v2.3` and later)

- Virtual audio cable. `SDR#`.






# Modems



- 300 bps AFSK for HF SSB
- **1200 bps Bell 202 AFSK VHF**
- 2400 bps QPSK (MFJ-2400, etc.)
- 4800 bps 8PSK
- **9600 bps G3RUH**

Receive only:


- AIS – for tracking ships
- Emergency Alert System (EAS) Specific Area Message Encoding (SAME)




| ← Voice → |



## Modem Audio Spectrum



1200 bps AFSK (Bell 202)



2400 bps PSK (V.26 / Bell 201)

MFJ-2400, AEA PK232-2400,  
Kantronics KPC-2400



9600 bps ("G3RUH")

Very low out to about 5 kHz.

Speaker cuts off below about 300  
Hz to eliminate CTCSS.




9600 bps



K9NG G3RUH et al – around 1988

About 5 kHz of audio bandwidth.

Will not work with microphone and speaker connections.




Squelch/COR		"Data Out 1200" (Receive Audio)
"DATA Out 9600" (FM Discriminator)		PTT
GND/COM		"Data In" (Transmit Audio)

Stephen H. Smith    WA8LMF@aol.com    10 March 2011

# Emergency Alert System



National Weather Service - more than 1000 stations - around 162 MHz.



Encoded:

ZCZC-WXR-RWT-020103-020209-020091-020121-029047-029165-029095-029037+0030-1051700-KEAX/NWS

Translated:

The National Weather Service in Kansas City/Pleasant Hill, MO has issued a Required Weekly Test valid until 01:30 PM for the following counties in Kansas: Johnson, Leavenworth, Miami, Wyandotte, and for the following counties in Missouri: Cass, Clay, Jackson, Platte. (KEAX/NWS)


# DTMF decode / encode

Received tone sequences are converted to packet like:

```
DTMF>APDW15:t12345#
```

Transmit tones by putting DTMF in the destination address.

```
WB2OSZ>DTMF:123 456
```






# Speech Synthesizer

Any packet with SPEECH is sent to a user-supplied script which can invoke a text-to-speech synthesizer.

```
WB2OSZ>SPEECH:Hello, World!
```

Configuration file example:

```
CBEACON dest=SPEECH  
info="Club meeting tonight  
at 7 pm."
```




# Send Morse Code



Any packet with MORSE as the destination is sent as Morse Code.


```
WB2OSZ>MORSE:CQ CQ
```






# Beacons


- Periodic position or object packets.
- GPS location - tracker.
- “Custom” - invoke user script.
- Weather. wxnow.txt



# Telemetry Tool Kit




- Building blocks for your own customized solutions.
- User-defined script to generate content.
- Raspberry Pi A/D converter example.



# APRStt Gateway




Converts Touch Tone sequences into APRS objects.





Tones 3 1 2 #



APRS  
Object Report




Synthesized  
Speech


“Canoe 12 is at  
checkpoint 3.”




APRStt  
Gateway



# Digital Repeater “digipeater”



- Extends range.
- Usually single frequency.
- Store and Forward.
- Dire Wolf: Multiple radios & routing between radio channels with filtering.




# Internet Gateway “IGate”

Connect disjoint radio networks.

Should be two way.

View APRS activity with web browser at

- [aprs.fi](http://aprs.fi)
- [findu.com](http://findu.com)
- [aprsdirect.com](http://aprsdirect.com)





# APRS "Messages"

Two way IGate stations required.





IGate A

IGate B



# Application Interfaces

- KISS and AGW network interfaces.
  - AGW interface allows access to more brains in the TNC such as connected mode.
- Applications attached by:
  - RS-232 Serial Port.
  - TCP/IP ( Ethernet, WIFI )
  - Bluetooth.
- Many simultaneous applications.






# Building a Better Demodulator



# Audio Frequency Shift Keying


- 1200 bits per second, 1200 & 2200 Hz.



- Which of the two tones is present?



# How to Demodulate AFSK





# After much reading & experimenting

- OK with perfect signals.
- Not so good with real-world signals.
- Why?



# WA8LMF TNC Test CD

- Los Angeles, afternoon rush hour, frequency completely saturated.
- Track 1: 25 minutes of flat audio from the discriminator.
- Track 2: De-emphasis to mimic typical receiver. (explained later)
- The de facto standard for measuring demodulator performance.

More details, see: [A-Closer-Look-at-the-WA8LMF-TNC-Test-CD.pdf](#)



# TNC Test CD Results


Do not take too seriously. Collected by different people, at different times, under different conditions. Most don't specify Track 1 / Track 2.

■ Linux PC multimon	*	130	
■ Linux PC soundmodem	*	412	
■ AGWPE	*	500	
■ AEA PK90		728	
■ TNC-X		818	
■ MFJ-1274		883	
■ AX25 Java Soundcard Modem	*	964	
■ KPC-3 (non-plus)		967, 986	
■ SCS Tracker DSP TNC 1.5s		988 / 943	(track 1/2)
■ Dire Wolf 1.7	*	1014 / 1000	(track 1/2)
■ UZ7HO Soundmodem 0.83b	*	1021	

\* = software on PC



# TNC Decoding Comparison




- Poor results from early software modems.
- Bad reputation.
- More recent software better than hardware modems.
- The tarnished reputation endures.



# VHF FM voice transceivers.


## Transmitter pre-emphasis

+ 6 dB per octave.



## Receiver de-emphasis


- 6 dB per octave





# Transmit / Receive mismatch

Flat on transmit.




Higher frequency weaker.





# Transmit / Receive mismatch



Flat on receive.


Higher frequency is stronger .










# Transmit / Receive mismatch

- Less reliable.
- Automatic gain control?
- Better but... AGC time ... noise






# Multiple demodulators.





# Multiple Gains for One Tone.

- Multiple fixed gains.



Less compute power needed.



# AX.25 + FEC = FX.25

2006 – Stensat Group – Satellites

- 64 bit pattern to identify the format of the data to follow.
- The normal AX.25 frame, including the FCS, and surrounding “flag” patterns.
- Parity check bytes.

8 bytes	32 To 239 bytes	16, 32, or 64 bytes
<b>Correlation Tag</b>	<b>Data (Normal AX.25 Frame)</b>	<b>Parity Check</b>




# AX.25 + FEC = FX.25


Tag Number	Correlation Tag Value	Data Bytes	Check Bytes	Number of Defective Bytes that can be repaired.
0x01	0xB74DB7DF8A532F3E	239	16	8
0x02	0x26FF60A600CC8FDE	128	16	8
0x03	0xC7DC0508F3D9B09E	64	16	8
0x04	0x8F056EB4369660EE	32	16	8
0x05	0x6E260B1AC5835FAE	223	32	16
0x06	0xFF94DC634F1CFF4E	128	32	16
0x07	0x1EB7B9CDBC09C00E	64	32	16
0x08	0xDBF869BD2DBB1776	32	32	16
0x09	0x3ADB0C13DEAE2836	191	64	32
0x0A	0xAB69DB6A543188D6	128	64	32
0x0B	0x4A4ABEC4A724B796	64	64	32



# FX.25 Improvement for APRS



# FX.25 Improvement for traditional Packet Radio





# Summary

- Ignore the advice from around the turn of the Century
- You don't need to spend \$200 on a box from the 1980's to get started with APRS / Packet Radio.
- Free Open Source Software:
  - Better Performance
  - More Features
  - Lower Cost



# Questions?

For more information:

<https://github.com/wb2osz/direwolf>

<https://groups.io/g/direwolf>

wb2osz @ arrl . net

- APRS is a registered trademark of APRS Software and Bob Bruninga, WB4APR. <http://www.aprs.net>
- Linux is a registered trademark owned by Linus Torvalds.